

LoRa Panic Button with Confirmation

OVERVIEW

The purpose of installing a LoRa based Panic Button Security Solution on the premise is to:

- Raise Alarm in real time
- Emergency Alarm with Acknowledgement
- Notify Responders
- Seek instant Assistance

KEY FEATURES

- 5 Years Battery Life
- Dust- and Waterproof
- Accidental Push Protection
- Built-In Confirmation Alarm
- Alarm message on Button Press
- Regular Heartbeat with Battery Status
- Secure Data Transmission
- Configurable in real-time with OTA Commands

SPECIFICATIONS

Model No.	MTC-PB01, 02
Enclosure Size	95 x 95 x 40 mm
Net Weight	184 g
Ingress Protection	IP67
Operating Temperature	-18°C to +55°C
RF Output	14 dBm
Battery Life	5 Years

MUTELCOR 



APPLICATION

- Educational Institutions
- Villas/Apartments
- Manufacturing Units
- Shopping Malls
- Hotels
- Hospitals
- Airports
- Banks
- Museums

LoRa Frequency	EU863-870 (CE-Certified) IN865-867 (ETA-Certified) US902-928 AU915-928 AS923 -1, -2, -3, -4 KR920-923
SF Supported	7 - 12
OTAA and ADR	Compliant
Voltage	3V (2 x AA-Alkaline Battery)